



HC9 Series HIGH CURRENT 9 Power Inductors

Description

- 155°C maximum total temperature operation
- Surface mount inductors designed for higher speed switch mode applications requiring lower inductance, low voltage and high current
- Design utilizes high temperature powder iron material with a non-organic binder to eliminate thermal aging
- Inductance Range from 0.2 uH to 47.0 uH
- Current Range from 95.0 Amps to 3.65 Amps
- Frequency Range 1kHz to 500kHz

Applications

- Next generation processors
- High current DC-DC converters
- VRM, multi-phase buck regulator
- PC. Workstations, Routers, Servers

Environmental Data

- Storage temperature range: -40°C to +155°C
- Operating temperature range: -40°C to +155°C (range is application specific)
- Solder reflow temperature: +260°C max for 10 seconds maximum





Packaging

Supplied in tape and reel packaging, 450 parts per reel

Part Number	Rated Inductance µH	OCL (1) nominal +/-15% µH	Irms (2) Amperes (Typ.)	Isat (3) Amperes 20% rolloff	Isat (4) Amperes 30% rolloff	DCR (mΩ) max. @ 20°C	Volts (5) µSec (VµS)
HC9-R20-R	0.20	0.218	46.7	65	95	0.50	2.87
HC9-R47-R	0.47	0.544	33.7	40	57	0.88	4.78
HC9-1R0-R	1.0	1.04	23.7	28	41	1.87	6.70
HC9-1R5-R	1.5	1.70	21.0	22	32	2.27	8.46
HC9-2R2-R	2.2	2.53	17.2	18	26	3.37	10.4
HC9-3R3-R	3.3	3.52	14.3	15	22	4.87	12.4
HC9-4R3-R	4.3	4.67	13.0	13.2	19.1	5.90	14.4
HC9-6R8-R	6.8	7.45	10.3	11.4	15.1	9.40	18.1
HC9-100-R	10.0	10.9	8.50	8.6	12.5	14.0	22.0
HC9-220-R	22.0	22.4	6.30	6.0	8.7	25.7	31.5
HC9-330-R	33.0	34.5	4.42	4.8	7.0	48.8	37.3
HC9-470-R	47.0	49.2	3.65	3.9	5.7	72.3	44.8

1) Test Parameters: 100KHz, 1.0Vrms

2) Irms Amperes for approximately ΔT of 40°C without core loss. De-rating is necessary for AC currents. PCB layout, trace thickness and width, airflow, and proximity of other heat generating components will affect the temperature rise. It is recommended that the temperature of the part not exceed 155°C under worst case conditions verified in the end application.

- 3) Peak current for approximately 20% rolloff @20°C 4) Peak current for approximately 30% rolloff @20°C 5) Applied Volt-Time product (V-µS) across the inductor. This value represents the applied V- μ S at operating frequency necessary to generate additional core loss which contributes to the 40°C temperature rise. De-rating of the Irms is required to prevent excessive temperature rise. The 100% V-uS rating is equivalent to a ripple current lp-p of 20% of lsat (30% rolloff option).

Part number definition:

First 3 characters = Product code and size. Last 3 characters = Inductance in μH . R = decimal point.


If no R is present third character = # of zeros.




Inselkammerstraße 10 D-82008 Unterhaching Tel.: +49 (0)89 614503 10 URL: www.hv-line.de

Gründenstrasse 10 CH-8247 Flurlingen Tel.: +41 (0)52 647 42 00 Fax: +49 (0)89 614503 20 Fax: +41 (0)52 647 42 01 E-Mail: power@hy-line.de E-Mail: power@hy-line.ch URL: www.hv-line.ch

Mechanical Diagrams













Packaging Information



Dimensions in Millimeters


Rolloff



Core Loss

Irms DERATING WITH CORE LOSS

% of Applied Volt-u-Seconds





POWER COMPONENTS Inselkammerstraße 10 D-82008 Unterhaching Tel.: +49 (0)89 614503 10

URL: www.hy-line.de

Gründenstrasse 10 CH-8247 Flurlingen Tel.: +41 (0)52 647 42 00 Fax: +49 (0)89 614503 20 Fax: +41 (0)52 647 42 01 E-Mail: power@hy-line.de E-Mail: power@hy-line.ch URL: www.hy-line.ch

PM-4125 8/06

Visit us on the Web at www.cooperbussmann.com

© Cooper Electronic Technologies 2006 1225 Broken Sound Pkwy. Suite F Boca Raton, FL 33487 Tel: +1-561-998-4100 Toll Free: +1-888-414-2645 Fax: +1-561-241-6640

This bulletin is intended to present product design solutions and technical information that will help the end user with design applications. Cooper Electronic Technologies reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Cooper Electronic Technologies also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.

Life Support Policy: Cooper Electronic Technologies does not authorize the use of any of its products for use in life support devices or systems without the express written approval of an officer of the Company. Life support systems are devices which support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.